

Technical data sheet

Plug-in arrester, total spark gap between N and PE 255 V

Item number: 5095603



Plug-in total discharge gap for use between neutral lines (N) and protector (PE)
Suitable for use in combination with:

- CombiController, type V 25-B+C
- SurgeController, type V 20-C
- SurgeController, type V 10-C
- * Complete = Plug-in arrester and base



Master data

Item number	5095603
Type	C 25-B+C 0
Description 1	Lightning current conductor
Description 2	choose N against PE
Manufacturer	OBO
Dimension	255V
Smallest sales unit	1
Unit of quantity	Piece
Weight	5.3 kg
Weight unit	kg/100 pc.


Technical data sheet

Plug-in arrester, total spark gap between N and PE 255 V

Item number: 5095603



Technical data



Arrester surge current (8/20 μ s) [total]	30 kA
Response time	<100 ns
Blow-out	no
Version for	1-pole cover; 255 V
Pole version	N/PE
Structural width in division units (division unit, 17.5 mm)	1
Operating temperature, max.	80 °C
Operating temperature, min.	-40 °C
Lightning surge current (10/350 μ s)	25 kA
Lightning surge current (10/350 μ s) [N/PE]	25 kA
Remote signalling	no
Follow current quenching capacity (eff) [N-PE]	0.1 kA
Maximum continuous voltage AC	255
Conductor cross-section, rigid (single-wire/multiwire), max.	35 mm ²
Conductor cross-section, rigid (single-wire/multiwire), min.	2.5 mm ²
Lightning protection zone LPZ	0→2
Max. mains-side overcurrent protection	160
Maximum back-up fuse	160 A
Maximum discharge current (8/20 μ s)	50 kA
Installation type	On basic element
Nominal discharge current (8/20 μ s)	30 kA
Nominal discharge current (8/20 μ s) [N-PE]	30 kA
Nominal voltage AC (50/60 Hz)	230 V
Network form	Other
Protection rating	IP20
Protection level	≤1,2
Signalling on device	None
SPD to EN 61643-11	Type 1+2
SPD to IEC 61643-1	Class I+II